



## Generator 4.5 kw a 5.4 kw AVR (Monophase)

ref. B401010104

Gasoline generator whose maximum power is 5.4 kw and in continuous 4.5 kw.

It has different sockets: 1 Schuko socket, 1 CE 230V 16A socket and 1 CE 230V 32A socket.

Strong and compact structure generator. It incorporates a handle and wheels for easy transport.

AVR: Automatic voltage regulator

Deposit of 25 liters.

**0,00 € tax excluded**

### Características principales

Peso (kg)	94
Longitud (mm)	727
Altura (mm)	670
Ancho total (mm)	515
Descripción	generador
Autonomía	10.15 Horas
Frecuencia (Hz)	50
Frecuencia (rpm)	3000
Nivel sonoro (dB)	97
Voltaje (V)	230
Potencia máxima nominal (LTP)	5.400
Potencia primaria nominal (PRP)	4.500
Fases	Monofásico
Fabricante del motor	PRAMAC
Carburante	Gasolina
Sistema de arranque	Eléctrico
Ruedas	si
Motor	PRAMAC AP190F

### Características ampliadas

Gasoline generator ideal for supplying energy wherever it is needed, it has a strong and compact structure. It also incorporates a folding handle and wheels for easy transport.

This generator contains a CONTROL PANEL that includes an ON and OFF switch, instrumentation (hour meter, voltmeter, frequency meter and fuel level) and tap protection.

It has different sockets: 1 Schuko socket, 1 CE 230V 16A socket and 1 CE 230V 32A socket.



- Brand: Pramac
- Engine: PRAMAC AP190F
- Continuous Power: 4,500
- Maximum Power: 5,400 W
- Tank capacity: 25 liters
- Autonomy: 10.15 hours
- Displacement: 420 cm<sup>3</sup>
- Aspiration: Natural
- Nominal operating speed: 3000 rpm
- Speed regulator: Mechanical
- Gasoline fuel
- Oil capacity: 1.1 L
- Starter system: Electric
- Weight: 94 kg

For more information, contact us.